

BATTERY CHARGER (30V/30A)



Salient Features:

- ⇒ Application for Battery Bank Charging
- ⇒ Works on 230V AC Mains
- ⇒ High Efficiency Battery charging
- ⇒ Suitable for battery banks of 30V
- ⇒ This System is capable of charging the batteries in constant voltage and constant current mode
- ⇒ Constant Voltage/Current selection through potentiometers
- ⇒ Wide input range high efficiency
- ⇒ Output Voltage adjust from 2V to 30V
- ⇒ Output Current adjust from 1A to 30A
- ⇒ MCB for I/P protection & ON/OFF purpose
- ⇒ Digital panel meters for O/P voltage and current display
- ⇒ Reverse polarity through fuse
- ⇒ Portable tool for battery maintenance

DATAERA EV SYSTEMS LLP

HYDERABAD

Phone: 8106339911

www.dataeraev.com

Email: dataeraev@gmail.com

SPECIFICATIONS	
Configuration	
BATTERY PACK	30V
BATTERY CHARGER	Charger, 30V with all necessary protections
CHARGER Specifications	
Voltage	30V Nominal
Current	10AH-300AH
Line Regulation	+/- 1%
Load Regulation	+/- 1%
Ripple	<1%
Constant Current Mode	
Line Regulation	+/- 1%
Load Regulation	+/- 1%
Ripple	<1%
General	
Input Voltage	230V AC \pm 10%, 1 phase, 50Hz
Input Supply protection and control	MCB
Output supply protection and control	Overload, over-voltage, Short-circuit Protections
Indicators	output voltage, charging current
Stabilization	Output DC supply will be stable against variations in input mains AC supply.
Cabinet	Charger housed in a cabinet with suitable output terminals.
Dimensions	480mm W x 460mm D x 200mm H (Approx)
Operating Temperature	0°C to + 55 °C

DATAERA EV SYSTEMS LLP

HYDERABAD

Phone: 8106339911

www.dataeraev.com

Email: dataeraev@gmail.com