

CELL BOOSTER (15V/120A)



Salient Features:

- ⇒ Application for Battery Bank Charging
- ⇒ Works on 230V AC Mains
- ⇒ High Efficiency Battery charging
- ⇒ Suitable for battery banks of 12V
- ⇒ This System is capable of charging the batteries in constant voltage and constant current mode
- ⇒ Constant Voltage/Current selection through potentiometers
- ⇒ Wide input range high efficiency
- ⇒ Output Voltage adjust from 2V to 15V
- ⇒ Output Current adjust from 1A to 50A
- ⇒ MCB for I/P protection & ON/OFF purpose
- ⇒ Digital panel meters for O/P voltage and current display
- ⇒ Reverse polarity through fuse
- ⇒ Portable tool for battery maintenance

DATAERA EV SYSTEMS LLP

HYDERABAD

Phone: 8106339911

www.dataeraev.com

Email: dataeraev@gmail.com

SPECIFICATIONS	
Configuration	
BATTERY PACK	15V
BATTERY CHARGER	Cell Booster, 15V with all necessary protections
CHARGER Specifications	
Voltage	15V Nominal
Current	1A-50A
Line Regulation	+/- 1%
Load Regulation	+/- 1%
Ripple	<1%
Constant Current Mode	
Line Regulation	+/- 1%
Load Regulation	+/- 1%
Ripple	<1%
General	
Input Voltage	230V AC $\pm 10\%$, 1 phase, 50Hz
Input Supply protection and control	MCB
Output supply protection and control	Overload, over-voltage, Short-circuit Protections
Indicators	output voltage, charging current
Stabilization	Output DC supply will be stable against variations in input mains AC supply.
Cabinet	Charger housed in a cabinet with suitable output terminals.
Dimensions	400mm W x 350mm D x 150mm H (Approx)
Operating Temperature	0°C to + 55 °C

DATAERA EV SYSTEMS LLP

HYDERABAD

Phone: 8106339911

www.dataeraev.com

Email: dataeraev@gmail.com